

Junistar Lux Square



Single or double downlight for indoor use. Junistar Lux Square emits a harmonious, flicker-free light with excellent colour rendering. Its patented, adjustable 30-degree tilt function in all directions. It includes a junction box that provides strain relief for several types of cables, as well as fixation for plastic tubing.

Galerie de produits et d'environnements



Article		Protection	Convertisseurs	Montage/Connexion	Dimensions
	902605 Junistar Lux Square Noir 580lm 2700K Ra 98 DALI-2 8W LED 73 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	DALI-2	Encastré, Indoor Linect 5 pôles / bornier sans vis	L95 x W95 x H50
	902587 Junistar Lux Square Noir 580lm 2700K Ra 98 Coupure de phase 8W LED 73 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor / Outdoor Bornier sans vis	L95 x W95 x H50
	902596 Junistar Lux Square Noir 2X 1160lm 2700K Ra 98 Coupure de phase 17W LED 68 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
	902611 Junistar Lux Square Acier brossé 2X 1160lm 2700K Ra 98 DALI-2 17W LED 68 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	DALI-2	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
	902584 Junistar Lux Square Acier brossé 580lm 2700K Ra 98 Coupure de phase 8W LED 73 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L95 x W95 x H50
	902593 Junistar Lux Square Acier brossé 2X 1160lm 2700K Ra 98 Coupure de phase 17W LED 68 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50

Article		Protection	Convertisseurs	Montage/Connexion	Dimensions
	902581 Junistar Lux Square Blanc 580lm 2700K Ra 98 Coupure de phase 8W LED 73 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor / Outdoor Bornier sans vis	L95 x W95 x H50
	902590 Junistar Lux Square Blanc 2X 1160lm 2700K Ra 98 Coupure de phase 17W LED 68 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
	902606 Junistar Lux Square Noir 590lm 3000K Ra 98 DALI-2 8W LED 74 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	DALI-2	Encastré, Indoor Bornier sans vis	L95 x W95 x H50
	902615 Junistar Lux Square Noir 2X 1180lm 3000K Ra 98 DALI-2 17W LED 69 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	DALI-2	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
	902588 Junistar Lux Square Noir 590lm 3000K Ra 98 Coupure de phase 8W LED 74 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor / Outdoor Bornier sans vis	L95 x W95 x H50
	902597 Junistar Lux Square Noir 2X 1180lm 3000K Ra 98 Coupure de phase 17W LED 69 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50

Article	Protection	Convertisseurs	Montage/Connexion	Dimensions
 902585 Junistar Lux Square Acier brossé 590lm 3000K Ra 98 Coupure de phase 8W LED 74 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L95 x W95 x H50
 902594 Junistar Lux Square Acier brossé 2X 1180lm 3000K Ra 98 Coupure de phase 17W LED 69 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
 902582 Junistar Lux Square Blanc 590lm 3000K Ra 98 Coupure de phase 8W LED 74 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor / Outdoor Bornier sans vis	L95 x W95 x H50
 902591 Junistar Lux Square Blanc 2X 1180lm 3000K Ra 98 Coupure de phase 17W LED 69 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50
 902589 Junistar Lux Square Noir 620lm 4000K Ra 98 Coupure de phase 8W LED 78 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor / Outdoor Bornier sans vis	L95 x W95 x H50
 902598 Junistar Lux Square Noir 2X 1240lm 4000K Ra 98 Coupure de phase 17W LED 73 lm/W SDCM:1 L90/B10>100,000	Classe II SELV IP44/IP20	Coupure de phase	Encastré, Indoor Bornier sans vis	L175 x W95 x H50

Article	Beam: 42°, Directe, Reflector	Protection	Convertisseurs	Montage/Connexion	Dimensions
	902583	Classe II SELV	Coupure de phase	Encastré, Indoor / Outdoor	L95 x W95 x H50
	Junistar Lux Square Blanc 620lm 4000K Ra 98 Coupure de phase 8W LED 78 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	IP44/IP20		Bornier sans vis	
	902592	Classe II SELV	Coupure de phase	Encastré, Indoor	L175 x W95 x H50
	Junistar Lux Square Blanc 2X 1240lm 4000K Ra 98 Coupure de phase 17W LED 73 lm/W SDCM:1 L90/B10>100,000 Beam: 42°, Directe, Reflector	IP44/IP20		Bornier sans vis	
Accessoires					
	903256				L140 x W140 x H4
	Soft Square Noir 1X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	903257				L258 x W140 x H4
	Soft Square Noir 2X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	903259				L376 x W140 x H4
	Soft Square Noir 3X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	820489				L220 x W75 x H34
	Sensor Dim Box Blanc 200VA				
	903254				L140 x W140 x H4
	Soft Square Blanc 1X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	903255				L258 x W140 x H4
	Soft Square Blanc 2X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	903258				L376 x W140 x H4
	Soft Square Blanc 3X Cadre for Soft Square, Junistar Lux Square & Junistar Square Isosafe DimToWarm				
	820090				L250 x W13 x H13
	Boîtier d'éclairage de secours Adapter kit downlight				

Article	Protection	Convertisseurs	Montage/Connexion	Dimensions
 8246094364 Boîtier d'éclairage de secours On-Off/Coupure de phase / EM Selvtest, Secours 3 heures				L270 x W75 x H35
 8246094500 Boîtier d'éclairage de secours Alim. DALI / EM DALI/Self test, Secours 3 heures				L270 x W75 x H35

• = Cet article est produit sur commande, avec un délai de livraison prévu de 3-4 semaines.