

# Sense 300x300



Sense luminaire used as replacement or alternative for a normal downlight. Very low profile and quick connection between luminaire and driver as well as tool-free connection in junction box with loop for easy and quick installation. High efficiency up to 95 lm/W and low glare rating makes Sense the obvious choice in many applications.

# Sense 300x300



## Product- and environment images



Article	Protection	Control gear	Mounting/Connection	Dimensions
 <p>212145  <b>Sense 300X300 White 2330lm</b>  <b>3000K Ra&gt;80 DALI-2 / Push Dim</b>  <b>20W LED</b>                      117 lm/W SDCM:3                      L80/B20&gt;100,000, L90&gt;50,000                      Direct, Opal</p>	<b>Class II SELV</b> <b>IP54/IP20</b> <b>IK08</b>	DALI-2 / Push Dim	Recessed, Indoor 5 pol Linect / screwless terminal block	L300 x W300 x H25
 <p>212140  <b>Sense 300X300 White 2330lm</b>  <b>3000K Ra&gt;80 Trailing edge</b>  <b>20W LED</b>                      117 lm/W SDCM:3                      L80/B20&gt;100,000, L90&gt;50,000                      Direct, Opal</p>	<b>Class II SELV</b> <b>IP54/IP20</b> <b>IK08</b>	Trailing edge	Recessed, Indoor 3 pol Linect / screwless terminal block	L300 x W300 x H25
 <p>212274  <b>Sense 300X300 White 2480lm</b>  <b>4000K Ra&gt;80 DALI-2 / Push Dim</b>  <b>20W LED</b>                      124 lm/W SDCM:3                      L80/B20&gt;100,000, L90&gt;50,000                      Direct, Opal</p>	<b>Class II SELV</b> <b>IP54/IP20</b> <b>IK08</b>	DALI-2 / Push Dim	Recessed, Indoor 5 pol Linect / screwless terminal block	L300 x W300 x H25
 <p>212273  <b>Sense 300X300 White 2480lm</b>  <b>4000K Ra&gt;80 Trailing edge</b>  <b>20W LED</b>                      124 lm/W SDCM:3                      L80/B20&gt;100,000, L90&gt;50,000                      Direct, Opal</p>	<b>Class II SELV</b> <b>IP40/IP20</b> <b>IK08</b>	Trailing edge	Recessed, Indoor 3 pol Linect / screwless terminal block	L300 x W300 x H25
<b>Accessories</b>				
 <p>820489  <b>Sensor Dim Box White 200VA</b></p>				L220 x W75 x H34
 <p>8246094429  <b>Emergencybox Driver DALI / EM Self test, DALI Emergency 3 hours</b></p>				L270 x W75 x H35
 <p>8246094364  <b>Emergencybox On-Off/Trailing edge / EM Self test, Emergency 3 hours</b></p>				L270 x W75 x H35
 <p>8246094500  <b>Emergencybox Driver DALI / EM DALI/Self test, Emergency 3 hours</b></p>				L270 x W75 x H35