

Sense Pro PIR



The Sense Pro PIR comes complete with driver, PIR sensor, cable and plug. The PIR sensor is discreetly located at the edge of the frame. The light is activated by movement and turns off automatically after a predetermined period of time to provide good energy savings. The sensor does not detect movement through walls or doors. The PIR sensor also has an adjustable daylight sensor, so you can choose not to turn on lighting when there is sufficient daylight. Sense PIR can act as a master, controlling up to 3 other Sense panels (slaves). Sense Opalprism PIR can be mounted on ceilings with visible T-rails without accessories and on ceilings with concealed T-rails with accessories.

Sense Pro PIR











Product- and environment images





Article codes



Article	Protection	Control gear	Mounting/Connection	Dimensions
 <p>212323</p> <p>Sense Opalprism 300x1200 White</p> <p>3880lm 3000K Ra>80 PIR Sensor</p> <p>34W LED</p> <p>114 lm/W SDCM:3</p> <p>L80/B20>100,000</p> <p>Opalprism</p>	<p>Class II</p> <p>IP20</p> <p>IK10</p>	PIR Sensor	<p>Recessed, Indoor</p> <p>Cable 2m</p> <p>Includes driver, cable and plug</p>	L1197 x W297 x H44
 <p>212680</p> <p>Sense Pro 600x600 White 4340lm</p> <p>3000K Ra>80 PIR Sensor</p> <p>35W LED</p> <p>124 lm/W SDCM:3</p> <p>L80/B20>100,000, L90>50,000</p> <p>Beam: 110°, Direct, Opalprism</p>	<p>Class II</p> <p>IP40/IP20</p> <p>IK06</p>	PIR Sensor	<p>Recessed</p> <p>Cable 2m</p> <p>Includes driver, cable and plug</p>	L597 x W597 x H44
 <p>212324</p> <p>Sense Opalprism 300x1200 White</p> <p>4060lm 4000K Ra>80 PIR Sensor</p> <p>34W LED</p> <p>119 lm/W SDCM:3</p> <p>L80/B20>100,000</p> <p>Opalprism</p>	<p>Class II</p> <p>IP20</p> <p>IK10</p>	PIR Sensor	<p>Recessed, Indoor</p> <p>Cable 2m</p> <p>Includes driver, cable and plug</p>	L1197 x W297 x H44
 <p>212681</p> <p>Sense Pro 600x600 White 4610lm</p> <p>4000K Ra>80 PIR Sensor</p> <p>35W LED</p> <p>132 lm/W SDCM:3</p> <p>L80/B20>100,000, L90>50,000</p> <p>Beam: 110°, Direct, Opalprism</p>	<p>Class II</p> <p>IP40/IP20</p> <p>IK06</p>	PIR Sensor	<p>Recessed</p> <p>Cable 2m</p> <p>Includes driver, cable and plug</p>	L597 x W597 x H44
Accessories				
 <p>212256</p> <p>Sense 600x600 White Surface frame</p>				L604 x W604 x H48
 <p>212257</p> <p>Sense 300x1200 White Surface frame</p>				L1203 x W303 x H47
 <p>8249045006</p> <p>Sense 600x600 White Plaster board/Troldtekt Recessed frame</p>				L640 x W640 x H40
 <p>212170</p> <p>Sense 2m Wire kit</p>				L2000

Article codes



Article	Protection	Control gear	Mounting/Connection	Dimensions
 212176 Sense 600x600 Concealed grid Bracket				L44 x W65 x H18
 212177 Sense 600x600 Asymmetric Bracket				L44 x W5 x H2.5