

Connect Driver Wireless



Turn a standard SG luminaire into SG Connect-compatible. Driver Kit Wireless must be used in combination with an SG Connect Sensor product or Connect Switch. The light will come on when movement is detected and will switch off after a fixed time period, helping to save energy. The lighting control is easy to configure using the SG Connect Commissioning App, and the various devices communicate wirelessly using Zigbee. • Built-in Bluetooth for programming and Zigbee for communication with other devices in the Connect range. • Twist connector for connecting light source. • 300–1050mA for enhanced flexibility. • Max 36W. • 3-pole Linect mounting unit.

Connect Driver Wireless



Product- and environment images



Article	Protection	Control gear	Mounting/Connection	Dimensions
Drivers				
 820503 Driver kit Wireless 13W 300mA Connect 13W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820504 Driver kit Wireless 18W 500mA Connect 18W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820505 Driver kit Wireless 22W 600mA Connect 22W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820506 Driver kit Wireless 26W 700mA Connect 26W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820507 Driver kit Wireless 30W 800mA Connect 30W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820508 Driver kit Wireless 40W 1050mA Connect 40W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30
 820515 Driver kit Wireless 35W 900mA Connect 35W 100,000	Class II IP20	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L157 x W45 x H30