

# Rax Soft 170-200 Connect




Rax Soft 170-200 Connect is a flexible, high-performance downlight for public buildings, offices, corridors, and similar environments. It comes with an integrated SG Connect sensor for smart and energy-efficient lighting control. The sensor switches the light on when motion is detected and off after a defined time period, ensuring significant energy savings. It also features a built-in daylight sensor that can be activated to maintain the desired light level in its working area. Configuration is simple via the SG Connect Commissioning App, and the luminaire can be used as a standalone unit or as part of a larger system that can easily be expanded or reconfigured as needed. Rax Soft 170-200 Connect combines advanced optics with practical flexibility. It features optimized lens and reflector optics for excellent light control, and a satin matte reflector for maximum efficiency. The unique design allows installation in hole diameters from 170 to 200 mm and can be adapted to Ø150 mm holes with plate cut-out for the sensor box. The luminaire must be combined with a suitable driver kit according to the desired lumen output.

# Rax Soft 170-200 Connect



## Product- and environment images



Article	Protection	Control gear	Mounting/Connection	Dimensions
 <p>212902  <b>Rax Soft 170-200 Satin 3000K Ra&gt;80</b>  <b>Connect</b>  <b>LED</b>                      SDCM:2                      L90/B10&gt;100,000                      Beam: 62°, Direct, Satin Matt                      Reflector</p>	<b>Class II SELV</b> <b>IP44/IP20</b>	Connect	Recessed, Indoor Quick connector	Ø220 x H83
 <p>212903  <b>Rax Soft 170-200 Satin 4000K Ra&gt;80</b>  <b>Connect</b>  <b>LED</b>                      SDCM:2                      L90/B10&gt;100,000                      Beam: 62°, Direct, Satin Matt                      Reflector</p>	<b>Class II SELV</b> <b>IP44/IP20</b>	Connect	Recessed, Indoor Quick connector	Ø220 x H83
<b>Drivers</b>				
 <p>820555  <b>Driver kit Rax Soft Sensor 300mA</b>  <b>Connect</b>  <b>12W</b>                      100,000</p>	<b>Class II</b> <b>IP20</b>	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L201 x W75 x H33
 <p>820556  <b>Driver kit Rax Soft Sensor 500mA</b>  <b>Connect</b>  <b>19W</b>                      100,000</p>	<b>Class II</b> <b>IP20</b>	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L201 x W75 x H33
 <p>820557  <b>Driver kit Rax Soft Sensor 700mA</b>  <b>Connect</b>  <b>27W</b>                      100,000</p>	<b>Class II</b> <b>IP20</b>	Connect	Recessed, Indoor 3 pol Linect / screwless terminal block	L201 x W75 x H33
<b>Accessories</b>				
 <p>900109  <b>Reliefplate</b></p>				L400 x W400 x H1
 <p>8246094364  <b>Emergencybox On-Off/Trailing edge / EM Self test, Emergency 3 hours</b></p>				L270 x W75 x H35